

## JUMO diraTRON DR100 – Universal controller for mounting on DIN rail 35 mm

- Universal analog input
- Temperature difference measurement
- Fast wiring due to spring-cage terminals
- Connection of up to 10 devices next to one another via the rear wall bus
- Digital output can also be used as transmitter supply
- Analog output optionally as actual value, setpoint value, or controller output
- RS485 interface
- Autotuning
- Service and operating hours counter

### Order details

<b>(1) Type</b>	
702061	JUMO diraTRON DR100 1x analog input, 1x relay (changeover contact), 1x DI, 1x DO
<b>(2) Version</b>	
0	Standard version
2	Customer-specific software
<b>(3) Option 1</b>	
0	None
1	Relay K2 (changeover contact) and Digital input 2
<b>(4) Option 2</b>	
0	none
3	Analog output
4	Interface RS485
<b>(5) Option 3</b>	
0	none
7	Interface RS485
<b>(6) Voltage supply</b>	
23	AC 110 ... 240 V +10/-15 %, 48 ... 63 Hz
36	DC 24 V -20/+25 %

### Order code

(1) (2) (3) (4) (5) (6)  
 /  -  -  -  -



### Stock versions

Order code	Part no.
702061/0-1-0-0-23	30063169
702061/0-1-0-0-36	30063143
702061/0-1-3-0-23	30063144
702061/0-1-3-0-36	30063116

### Accessories

Description	Part no.
USB cable, A connector to Micro-B connec length 3 m	00616250
Mounting rail rear wall terminal (device)	00763134
PUSH IN connection terminal	00764414

### Software

Description	Part no.
Setup JUMO diraTRON DR100	30071435